

LED

Dark Sky Friendly illumination



Architectural LED Luminaires Outdoor Wall Packs/Sconces



GENERAL SPECIFICATIONS:

- Die Cast Aluminum*.
- Energy Efficient LED Light Engines
- LEDs from NICHIA, CREE, LUMILEDS, SAMSUNG, and OSRAM.
- Standard 5 Year Warranty.
Optional Pro Rated 10 Year Warranty.
- Nominal 140 Initial Lumens Per Watt.
- BUG Ratings/Photometry available on spec-sheets:
Visit www.eclipselightinginc.com
- Dunkirk-DL & Dunkirk-B Small, Legacy are ADA Compliant.

* NOTE: Florence and Liverpool are Formed Aluminum.

FIXTURE	Nominal LED Wattage	Emergency
Dresden-T	Selectable: 15W / 30W / 45W / 60W	N/A
Dunkirk-B	Small: 12W Medium: 30W / 50W Large: 80W / 120W	REL
Florence	Small: 15W Medium: 40W Large: 40W / 60W	REL
Glasgow	30 Watt / 40 Watt / 50 Watt	EL / REL
Kiev	20 Watt / 30 Watt / 40 Watt	EL / REL
Legacy Wet	11 Watt / 14 Watt	REL
Liverpool	30 Watt	EL / REL
Munich	Small: 15W / 22W / 25W Large: 37W / 40W / 50W / 60W X-Large: 40W / 50W / 60W	EL / REL
Troy 3	30 Watt	N/A
Turin	20 Watt / 30 Watt / 40 Watt	EL

FIXTURES	SIZE (nominal)
DD-T = Dresden-T	9"W x 8"L x 6.7"H
DK-B = Dunkirk-B	Small: 5"W x 6"H x 3.4"D Medium: 7.6"W x 11"H x 4.5"D Large: 11"W x 13"H x 5.5"D
FR = Florence	Small: 14"W x 10"H x 10"D Medium: 18"W x 15"H x 16"D Large: 24"W x 20"H x 15"D
GW = Glasgow	18"W x 8"H x 9"D
KV = Kiev	18"W x 9"H x 9"D
LGC-W = Legacy Wet	Rectangle: 4.5"W x 14"H x 2.5"D Round: 5"W x 14"H x 2.75"D
LV = Liverpool	13"W x 13"H x 11.75"D
MU = Munich	Small: 8.75"W x 8.6"H x 9.5"D Large: 14.25"W x 9"H x 11"D X-Large: 18.25"W x 9"H x 11"D
TY3 = Troy 3	4.3" Diameter x 11.8"H
TU = Turin	18"W x 7"H x 9"D

- ① Options shown are not available for all fixtures listed. Please refer to the product specific spec-sheet for option availability.
- ② Consult Factory for additional Emergency Battery options not shown
- ③ Max mounting height of fixture is 18' (18 feet)
- ④ Max WHIP length of the REL is 8 feet.
- ⑤ Final selection of the Battery Pack under discretion of Factory

FINISH

- BK = Black
- BZ = Bronze
- PNA = Painted Natural Aluminum
- WH = White
- +NAT = Conformal Coating - Light Engine Only
- CC = Custom Color (Visit www.ralcolor.com)
— Provide RAL# or Make-to-Match Color Chip

DIMMING OPTIONS

- Note: 0-10V 100%-30% is Standard
- D7A = 0-10VDC LED Dimming Driver (100-10%)
- D7B = 0-10VDC LED Dimming Driver (100-1%)

CONTROL OPTIONS

- Note: See Accessory Options for Required Remote Controller
- 9328 = Photocell Button (120/277V)
- OCC = Occupancy Sensing | Motion Sensor Integral[Ⓜ]
— Microwave / Single Feed / 120/277V Only
— Standby Dim Level Presets: ON/OFF (0%/100%)
- BLD = Bi-Level Dimming | Motion Sensor Integral[Ⓜ]
— Microwave / Single Feed / 120/277V Only
— Standby Dim Level Presets:
10% / 20% / 30% (Standard) / 50%
- BLDA = Bi-Level Dimming | Motion Sensor Integral[Ⓜ]
— Ambient Light Sensing Feature (AMB)
— Microwave / Single Feed / 120/277V Only
— Standby Dim Level Presets:
10% / 20% / 30% (Standard) / 50%
— Bi-Level Control Initiated at AMB Light Level Preset
- BLS = Bi-Level Switching — Using 2 Drivers (2UNV)

MISC OPTIONS

- BB = Back Box
- FUS = Single Fusing
- DFUS = Double Fusing
- SG = 10KA Surge Protection (ANSI spec C62.41.2)
- TP = Tamperproof Screws

EMERGENCY BATTERY OPTIONS[Ⓜ] 50 55

No onsite Emergency Power (AC or DC) is provided

- GTD1 = Generator Transfer Device (Signify)
- GTD2 = Generator Transfer Device (LGTD)
— Shunt Relay w/Fire Alarm Override Input

Meets California Energy Commission Title 20: (CEC-400-2014-009-CMF) Efficiency Standards

- EL4W = Integral LED 4 Watt
- EL8W = Integral LED 8 Watt
- EL16W = Integral LED 16 Watt
- EL20W = Integral LED 20 Watt
- REL4W = Remote LED 4 Watt
- REL8W = Remote LED 8 Watt
- REL16W = Remote LED 16 Watt
- REL20W = Remote LED 20 Watt

Cold Weather Emergency Batteries:

Operating Temp: -20°C thru 50°C

NON-CEC Compliant

- EL10W-CW = Integral LED 10 Watt - Cold Weather
- EL23W-CW = Integral LED 23 Watt - Cold Weather
- REL10W-CW = Remote LED 10 Watt - Cold Weather
- REL23W-CW = Remote LED 23 Watt - Cold Weather

ACCESSORY OPTIONS (order as a separate line)

- 9002 = Tamperproof Screwdriver
- REMT = Remote Controller for Sensor Options

